

## X-NRI/EN Network Resource Interface

---

- Provides 4 AUX balanced audio input for digitalization of the external analog audio source and routing to the network
- Built-in 4G SD card as internal audio source
- 4 Ethernet interfaces allow communication of multiple X-DCS2000/EN
- Has 32 x dry contact control inputs and input faults can be monitored
- Has 2 x RS-485 communication terminals for integration with Fire Panel via protocol



X-NRI/EN Network Resource Interface is a universal interface of X-618 for external control access and audio extension. It is suitable to the needs of central interfaces management required by middle-to-large applications. The device provides 4 external audio source interfaces and 1 built-in audio source. These audio sources are network audio source which can be shared in the Ethernet.

### Functions

#### **BACKUP POWER SUPPLY**

X-NRI/EN applies main power supply and 24 VDC backup power supply. Through software configuration, the fault of power supply can be detected. By default the device is running on main power. When the main power is disabled, it automatically relays to backup power supply and the main power indicator on X-NRI/EN front panel turns yellow at the same time. As long as the main power resume to normal, the power supply switch back to main power.

#### **POWER SUPPLY PROTECTION**

X-NRI/EN has main power protection. When internal short circuit or other forms of malfunction come across, the main power supply will be cut off for protection of the device.

#### **SELF DETECTION**

By self detection function, X-NRI/EN can detect faults include Main/Backup power supply, system malfunction, and communication fault and has respective indicators on the front panel. When there is a fault, the fault indicator turns yellow and siren goes off to warn the operators and the fault status will be logged.

#### **EXTERNAL AUDIO SOURCE DELIVERY**

X-NRI/EN has 4 RCA terminals for external audio source input. They can be configured by system software in terms of On/Off, the name of audio, multicast address and the type of interfaces, etc. During installation, the external audio source is required physically connection with the inputs and by using X-SMART software, X-NPMI/EN and X-DCS2000/EN to select the target zones and audio, the audio source can be delivered.

External audio sources can be connected to X-NRI/EN directly such as CD or DVD. There are 4 balanced inputs for paging station connection and through dip switch on the right of rear panel, volume GAIN level can be adjusted and phantom power supply can be turned on/off. The power supply voltage of phantom power supply is DC 24V.

## VOICE ALARM

X-NRI/EN provides 32 x dry contact inputs for fire alarm integration. Through X-SMART software, voice alarm zones of each X-DCS2000/EN can be planned in accordance with fire alarm zones as well as the adjacent zones which required by international voice alarm standard. When fire alarm triggering the X-NRI/EN, it automatically communicate with the triggered X-DCS2000/EN and override the BGM broadcast by preserved voice message of emergency. When proceeding voice alarm in the zones on fire, X-DCS2000/EN can deliver the different evacuation message to preset adjacent zones.

## Technical Specifications

Parameter	Value
Main power supply	-100 - 240 V, 50/60 Hz
Backup power supply	DC 21.5 V 28.5 V
Main power fuse	T2 AL 250 V
Rated power	15 W
<b>Auxiliary input</b>	
Input channels	4
Input signal	1 V 0 dBV
Input impedance	20 kΩ
Frequency response	60 Hz - 16 kHz
S/N	> 85 dB
<b>Balanced Input</b>	
Input channels	4
Input signal	14 mV (-37 dBV) / 1 V(odBV)
Input impedance	20 kΩ
Phantom power supply	DC 24 V
Frequency response	60 Hz - 16 kHz
S/N	> 65 dB
<b>Control Terminal</b>	
Trigger inputs	32 inputs (can be monitored)

Trigger outputs (reserved)	8 outputs (NO, NC and COM)
Trigger outputs (reserved)	
Max working voltage	AC 250 V / DC 30 V
Max working current	2.5 A
<b>Others</b>	
Network interface	2.5 A
Number of ports	4
Audio Storage	4 GB SD card 1 GB Flash

### Working environment

Humidity	95 % (no condensation)
Operation temperature	-10 °C ~ +55 °C
Storage temperature	-40 °C ~ +70 °C

### Specification

Product dimensions (W×H×D)	482 × 88 × 420 mm
Package dimensions (W×H×D)	580 × 235 × 552 mm
Net weight	7.3 kg
Gross weight	10 kg

## Packing List

Component	Quantity
X-NRI/EN Network Resource Interface	1
Dry contact input terminals (8P)	8
Dry contact output terminals (6P)	4
Control terminal (8P)	1
Balanced input terminals (8P)	2
Power connector kit	1

Plastic foot	4
Network cable	1
AC Power cable	1
Fuse (2A)	1
Warranty card	1
Quality certificate	1
Product manual	1
Rack	2

## Order Information

Description	Ordering Information
X-NRI/EN Network Resource Interface	X-NRI/EN

### HoneywellAudiovisuals

No. 257, Junye Road  
Guangzhou GETDD East  
510530 China

Tel: +86 20 2839 9600

Fax: +86 20 2820 8706

[www.honeywellav.com](http://www.honeywellav.com)

1013703019 (A)\_EN2.1

Aug 2013

©2013 Honeywell International Inc.